



## Wired barreras detector AX-130TN

### DETECTION

|                      |                                     |
|----------------------|-------------------------------------|
| Detector type        | <b>Wired</b>                        |
| Nº de haces          | <b>2</b>                            |
| Angle detection      | <b>90° horizontal / 5° vertical</b> |
| Detection distance   | <b>40 m</b>                         |
| Detection speed      | <b>0,3 m/s ~ 2,4 m/s</b>            |
| Alarm period         | <b>2 s</b>                          |
| Detection technology | <b>Barreras</b>                     |

### AMBIENT

|                       |                       |
|-----------------------|-----------------------|
| Operating temperature | <b>-35 °C ~ 60 °C</b> |
| Degree of protection  | <b>IP65</b>           |
| Use                   | <b>Indoor-outdoor</b> |
| Maximum humidity      | <b>95%</b>            |

### POWER CONSUMPTION

|            |                    |
|------------|--------------------|
| Power mode | <b>DC</b>          |
| Voltage    | <b>10.5V ~ 28V</b> |
| Amperage   | <b>40mA</b>        |

### MATERIAL AND DIMENSIONS

|                       |                           |
|-----------------------|---------------------------|
| Installation          | <b>Wall / Post</b>        |
| Dimensions            | <b>65 x 170 x 69.5 mm</b> |
| Net weight            | <b>630 g</b>              |
| Weight with packaging | <b>1050 g</b>             |

### TECHNICAL SPECIFICATIONS

|                |                     |
|----------------|---------------------|
| LED indicators | <b>Yes</b>          |
| LED colors     | <b>Verde / Rojo</b> |
| Tamper         | <b>Yes</b>          |

### SENSOR

|                |                      |
|----------------|----------------------|
| Type of sensor | <b>Fotoeléctrico</b> |
|----------------|----------------------|

