



## Alarm box ARB1606



### POWER CONSUMPTION

|                 |               |
|-----------------|---------------|
| Voltage         | <b>12V</b>    |
| Consumption (w) | <b>0.2W</b>   |
| Amperage        | <b>1000mA</b> |

### MATERIAL AND DIMENSIONS

|              |                            |
|--------------|----------------------------|
| Installation | <b>Desktop</b>             |
| Dimensions   | <b>97.7 x 90.3 x 33 mm</b> |
| Net weight   | <b>2000 g</b>              |

### FEATURES

|               |                |
|---------------|----------------|
| Communication | <b>1 RS485</b> |
| DIP Switch    | <b>2-bit</b>   |

### ALARMS

|                        |                                |
|------------------------|--------------------------------|
| Alarm inputs / outputs | <b>16 Entradas / 6 Salidas</b> |
|------------------------|--------------------------------|

### AMBIENT

|                       |                       |
|-----------------------|-----------------------|
| Operating temperature | <b>-10 °C ~ 55 °C</b> |
| Maximum humidity      | <b>90%</b>            |

### GENERAL INFORMATION

|      |                  |
|------|------------------|
| Type | <b>Alarm box</b> |
|------|------------------|

