



## AJAX

### Transmitter via radio

### MULTITRANSMITTER-3EOL-B

#### POWER CONSUMPTION

|                 |                    |
|-----------------|--------------------|
| Power mode      | <b>AC</b>          |
| Voltage         | <b>100V ~ 240V</b> |
| Battery support | <b>Optional</b>    |
| Battery model   | <b>12V DC 7Ah</b>  |

#### AMBIENT

|                       |                       |
|-----------------------|-----------------------|
| Operating temperature | <b>-10 °C ~ 40 °C</b> |
| Degree of protection  | <b>IP40</b>           |
| Use                   | <b>Indoor</b>         |
| Maximum humidity      | <b>75%</b>            |

#### TECHNICAL SPECIFICATIONS

|                             |                                                      |
|-----------------------------|------------------------------------------------------|
| Compatibility               | <b>Central Ajax (as of OS Malevich 2.13) and ReX</b> |
| Tamper                      | <b>Yes</b>                                           |
| EOL resistors (end of line) | <b>Yes, triple</b>                                   |
| Conexión a detector         | <b>NC / NO / EOL / 2EOL / 3EOL</b>                   |

#### CERTIFICATION

|           |                |
|-----------|----------------|
| Grade     | <b>2</b>       |
| Normative | <b>EN50131</b> |

#### MATERIAL AND DIMENSIONS

|                       |                           |
|-----------------------|---------------------------|
| Dimensions            | <b>238 x 192 x 100 mm</b> |
| Net weight            | <b>800 g</b>              |
| Weight with packaging | <b>1130 g</b>             |
| Color                 | <b>Black</b>              |

#### VIA RADIO

|                       |                              |
|-----------------------|------------------------------|
| Frequency             | <b>868.0 MHz ~ 868.6 MHz</b> |
| Transmission distance | <b>Up to 2000 meters</b>     |
| Maximum power RF      | <b>Hasta 20 mW</b>           |

#### GENERAL INFORMATION

|      |                              |
|------|------------------------------|
| Type | <b>Transmitter via radio</b> |
|------|------------------------------|

#### ZONES

|                         |           |
|-------------------------|-----------|
| Maximum number of zones | <b>18</b> |
|-------------------------|-----------|

